

5805

NVR Switch



Key Vaule Highlight

- One mouse, One keyboard, One monitor, 16 units NVR

The operator can use one keyboard, monitor, and mouse to control 16 units NVR with 5805 NVR switch.

- Quick switch with hot key design.

The operator can quickly activate specific NVR on the monitor with mouse and keyboard

- Plug & play Setup

The user can complete the setup with simple plug the VGA output to the 5805 NVR switch, no need to configure each of the NVRs.

- Standalone solution

5805 NVR switch can make the regular operation of the IP surveillance without involving any PC platform.

Typical Application

Headquarter office

City Surveillance

Telecom

Logistics Center

and others

Specification

Rated Voltage and Power	
Rated Voltage	110V~240V, 47Hz~63Hz
Power	DC 9.0V
Video	
Video Standard	PAL or NTSC
NVR connector	16 x USB (Type A) 16 x VGA
Video Resolution	2048 x 1536
NVR selection	Hot-Key, Push Button
OS Supported	Embedded Linux, Linux, Windows, Mac OS
Monitors Supported	VGA or SVGA compatible monitor
Mechanical	
Dimensions (W x D x H) (excluding cabling)	420(L) x 40(H) x 180(W)mm
Weight	4.5kg
Environmental	
Operating temperature	+5 °C to +45 °C (+41 °F to +113 °F)
Storage temperature	-25 °C to +70 °C (-13 °F to +158 °F)
Relative humidity	Operating: <93 % non-condensing Storage: <95 % non-condensing
Ordering Information	
NVR Switch	5805

Guangzhou

No.3 East Alley, Guangfeng East Road,
Zengchen District, Guangzhou., 511300,
P.R.China
Tel: +86-20-8244-2660
Fax: +86-20-8274-5925
Email: sales@golbong.com

Shenzhen

1/F Block 295, Jiuwei, Xixiang Town,
Baoan District, Shenzhen, 518000,
P.R.China
Tel: +86-755-81465995
Fax: +86-755-81469770
Email:sales@golbong.com